



地址(Add):深圳福田区福华路福庆街鸿图大厦1602室
RM 1602, Hongtu Bldg, Fuhua Rd, Futian Region, Shenzhen China
电话(Tel): 0755-3600718 3758073 邮编(PC): 518033
传真(Fax): 0755-3376182 E-mail: szsunstr@public.szptt.net.cn
网址: [Http://www.sunstare.com/](http://www.sunstare.com/) 手机: (0)13902971329
西安办事处电话: (0)13609291696 191-8454356
北京办事处电话: (0)13501189838 191-8886650
上海办事处电话: (0)13701955389 191-3789221


SS0502

GENERAL DESCRIPTION: SS0502 IS AN INTEGRATED CIRCUIT PROVIDED WITH DIGITAL THERMOMETER FUNCTION. TEMPERATURE REANGING FROM -50°C TO $+50^{\circ}\text{C}$ IS DETECTED BY USE OF A THERMISTER AS A SENSOR AND TEMPERATURE IS DISPLAYED ON A LCD BY 0.2°C STEP.

FEATURE: MEASUREMENT OF TEMPERATURE (THERMISTER SEMITEC 103CT)

- MEASUREABLE RANGE: $-50^{\circ}\text{C} \sim +50^{\circ}\text{C}$ ($-58^{\circ}\text{F} \sim +122^{\circ}\text{F}$)
- RESOLUTION: 0.2°C (F)
- ACCIRACY: $\pm 1^{\circ}\text{C}$
- 3 1/2 + 7 INDICATORS, 1/2 DUTY LCD
- LOW POWER CONSUMPTION
- FEW EXTERNAL COMPONENTS
- EASINESS IN ADJUSTMENT
- SERIAL INTEFACD OUTPUT
- 1.5V BATTFF OPERATION

LCD FO





地址(Add):深圳福田区福华路福庆街鸿图大厦1602室
 RM 1602, Hongtu Bldg, Fuhua Rd, Futian Region, Shenzhen China
 电话(Tel): 0755-3600718 3758073 邮编(PC): 518033
 传真(Fax): 0755-3376182 E-mail: szsunstr@public.szptt.net.cn
 网址: <http://www.sunstare.com/> 手机: (0)13902971329
 西安办事处电话: (0)13609291696 191-8454356
 北京办事处电话: (0)13501189838 191-8886650
 上海办事处电话: (0)13701955389 191-3789221

FUNCTION DESCRIPTION



A THERMISTER IS USED FOR DETECTING TEMPERATURE AND CONVERT TO FREQUENCY. HIGH ACCURACY IS OBTAINED IN WIDE RANG OF $-50^{\circ}\text{C} \sim +50^{\circ}\text{C}$ BY PROVIDING NONLINEAR CORRECTION CIRUCIT FOR THERMISTER INSIDE THE IC.

ITEM	REMARKS
MEASWRABLE TEMPERATURE RANGE	$^{\circ}\text{C}$ $-49^{\circ}\text{C} \sim +49.8^{\circ}\text{C}$ $^{\circ}\text{F}$ $-57^{\circ}\text{C} \sim 121.8^{\circ}\text{F}$
SUITABLE THERMISTER (103CT)	$R_T = 10\text{K}\Omega \pm 5\%$ (AT 20°C) $B = 3270\text{K} \pm 2\%$
RESOLUTION	0.2°C DEGREE STEP
SAMPLING CYCLE	1 SECOND, 3 SECOND, 5 SECOND, 10 SECOND (DEFAULT 10 SEC)
OSCILLATION FREQUENCY: 16 KHZ	

TEMPERATURE ADJUSTMENT: ADJUSTMENT OF TEMPERATURE IS MADE BY ADJUSTING FUNDAMENTAL RESISTANCE AGAINST DISPERSION IN RESISTANCE VALUES OF THERMISTERS.

THE VALUE OF REF IS ADJUSTED TO COINCIDE WITH THE TEMPERATURE INDICATION A RESISTOR.

APPLICATION:




1: OSCR	16: SEG13	30: VEE
2: PWR	17: SEG12	31: VSS
3: SAMP1	18: SEG11	32: SELC
4: SAMP2	19: SEG10	33: INT
5: VCP	20: SEG 9	34: MD
6: T1	21: SEG 8	35: SHCK
7: T2	22: SEG 7	36: OSI
8: ADJ	23: SEG 6	
9: REF	24: SEG 5	
10: THER	25: SEG 4	
11: CAP	26: SEG 3	
12: VDD	27: SEG 2	
13: VCD	28: SEG 1	
14: COM2	29: COM 1	
15: SEG14		




地址(Add):深圳福田区福华路福庆街鸿图大厦1602室
 RM 1602,Hongtu Bldge,Fuhua Rd, Futian Region,Shenzhen China
 电话(Tel):0755-3600718 3758073 邮编(PC):518033
 传真(Fax):0755-3376182 E-mail:szsunstr@public.szptt.net.cn
 网址: Http://www.sunstare.com/ 手机:(0)13902971329
 西安办事处电话:(0)13609291696 191-8454356
 北京办事处电话:(0)13501189838 191-8886650
 上海办事处电话:(0)13701955389 191-3789221

DISPLAY FORMAT:






LCD FORMAT



LCD FORMAT



SUNSTAR 深圳市商斯达电子有限公司
SHENZHEN SUNSTAR ELECTRONICS CO.,LTD.

地址(Add):深圳福田区福华路福庆街鸿图大厦1602室
RM 1602,Hongtu Bldge,Fuhua Rd, Futian Region,Shenzhen China

电话(Tel):0755-3600718 3758073 邮编(PC):518033

传真(Fax):0755-3376182 E-mail:szsunstr@public.szptt.net.cn

网址:Http://www.sunstar.com.cn 手机:(0)13902971329

西安办事处电话:(0)13609291696 191-8454356

北京办事处电话:(0)13501189838 191-8886650

上海办事处电话:(0)13701953389 191-3780221

TEL: 0755-83387016 FAX:0755-83376182 E-MAIL:szss20@163.com




地址(Add): 深圳福田区福华路福庆街鸿图大厦1602室
 RM 1602, Hongtu Bldg, Fuhua Rd, Futian Region, Shenzhen China
 电话(Tel): 0755-3600718 3758073 邮编(PC): 518033
 传真(Fax): 0755-3376182 E-mail: szsunstr@public.szptt.net.cn
 网址: [Http://www.sunstare.com/](http://www.sunstare.com/) 手机: (0)13902971329
 西安办事处电话: (0)13609291696 191-8454356
 北京办事处电话: (0)13501189838 191-8886650
 上海办事处电话: (0)13701955389 191-3789221

SPECIFICATION

ELECTRICAL CHARACTERISTIC

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT
OPERATING VOLTAGE	VDD	1.2	1.5	2.0	VOLT
STANDBY CURRENT	Istd		5.0	10.0	μA
OPERATING TEMP	Top	-50		+50	$^{\circ}C$
STORAGE TEMP.	Istr	-50		+125	$^{\circ}C$
MEASURING CURRENT	I meas		50	80	μA



DICE SIZE :
SUBSTRATE CONNECTED TO VDD

PAD NO.	DESTINATION	X	Y	PAD NO.	DESTINATION	X	Y
1	OSCR	2402	2045	19	SEG10	412	105
2	PWR	2084	2045	20	SEG 9	591	105
3	SAMP1	1688	2045	21	SEG 8	913	105
4	SAMP2	1460	2045	22	SEG 7	1093	105
5	VCP	1219	2045	23	SEG 6	1411	105
6	T1	1036	2045	24	SEG 5	1590	105
7	T2	803	2045	25	SEG 4	1917	105
8	ADJ	648	2045	26	SEG 3	2088	105
9	REF	424	2045	27	SEG 2	2414	105
10	THER	65	2045	28	SEG 1	2659	105
11	CAP	69	1806	29	COM 1	2667	276
12	VDD	69	1621	30	VEE	2667	690
13	VCD	69	1324	31	VSS	2667	881
14	COM2	69	910	32	SELC(CF)	2667	1062
15	SEG14	69	742	33	INT	2667	1239
16	SEG13	69	715	34	MD	2667	1430
17	SEG12	69	315	35	SHCK	2667	1618
18	SEG11	69	105	36	OS'	2667	1825

SUNSTAR 深圳市商斯达电子有限公司
SHENZHEN SUNSTAR ELECTRONICS CO.,LTD.

集成电路
单片机

地址(Add):深圳福田区福华路福庆街鸿图大厦1602室
RM 1602,Hongtu Bldg,Fuhua Rd, Futian Region,Shenzhen China
电话(Tel):0755-3600718 3758073 邮编(PC):518033
传真(Fax):0755-3376182 E-mail:szsunstr@public.szptt.net.cn
网址: [Http://www.sunstare.com/](http://www.sunstare.com/) 手机:(0)13902971329
西安办事处电话:(0)13609291696 191-8454356
北京办事处电话:(0)13501189838 191-8886650
上海办事处电话:(0)13701955389 191-3789221

SUNSTAR 深圳市商斯达电子有限公司
SHENZHEN SUNSTAR ELECTRONICS CO.,LTD.

集成电路
单片机

地址(Add):深圳福田区福华路福庆街鸿图大厦1602室
RM 1602,Hongtu Bldg,Fuhua Rd, Futian Region,Shenzhen China
电话(Tel):0755-3600718 3758073 邮编(PC):518033
传真(Fax):0755-3376182 E-mail:szsunstr@public.szptt.net.cn
网址: [Http://www.sunstare.com/](http://www.sunstare.com/) 手机:(0)13902971325
西安办事处电话:(0)13609291696 191-8454351
北京办事处电话:(0)13501189838 191-8886651
上海办事处电话:(0)13701955389 191-378922

FUNCTION OF TERMINALS:

NAME OF TERMINALS	FUNCTION															
THER, CAP, REF	OSCILLATOR CIRCUIT FOR TEMPERATURE DETECTION															
CF	℃/℉ TERMINAL, DEFAULT (VSS) SELECT ℃															
MD, SHCK	SERIAL MEASUREMENT DATA OUTPUT TERMIAL MD=SERIAL DATA OUTPUT SHCK=SERIAL SHIFT CLOCK															
OSC, OSCR	OSCILLATOR CIRCUIT FOR SYSTEM CLOCK															
VCD, VCR	BOOSTER CAPACITOR CONNECTION TERMINAL															
VEE	LEVEL SHIFT (3V)															
COM1, COM2	LCD COMMENT DRIVE															
SEG1~SEG14	LCD SEGMENT DRIVE															
ADJ	ADJUST THE FIXED TEMPERATURE (ACTIVE HIGH)															
INT	SIGNAL TO INTERRUPT THE MPU.															
T1,T2	TEST INPUT TERMINAL															
SAMP1, SAMP2	PIN OPTION, SELET THE THERMISTOR SAMPLING CYCLE (DEFAULT 10S) <table><tr><th>SAMP1</th><th>SAMP2</th><th>SAMPLENG CYCLE</th></tr><tr><td>0</td><td>0</td><td>10S</td></tr><tr><td>0</td><td>1</td><td>1S</td></tr><tr><td>1</td><td>0</td><td>2S</td></tr><tr><td>1</td><td>1</td><td>5S</td></tr></table> 0:VSS 1:VDD	SAMP1	SAMP2	SAMPLENG CYCLE	0	0	10S	0	1	1S	1	0	2S	1	1	5S
SAMP1	SAMP2	SAMPLENG CYCLE														
0	0	10S														
0	1	1S														
1	0	2S														
1	1	5S														



地址(Add): 深圳福田区福华路福庆街鸿图大厦1602室
RM 1602, Hongtu Bldg, Fuhua Rd, Futian Region, Shenzhen China
电话(Tel): 0755-3600718 3758073 邮编(PC): 518033
传真(Fax): 0755-3376182 E-mail: szsunstr@public.szptt.net.cn
网址: [Http://www.sunstare.com/](http://www.sunstare.com/) 手机: (0)13902971329
西安办事处电话: (0)13609291696 191-8454356
北京办事处电话: (0)13501189838 191-8886650
上海办事处电话: (0)13701955389 191-3789221

LCD FORMAT




Fig. 2

Segment pair


	N ₁	N ₂	N ₃	N ₄	N ₅	N ₆	N ₇	N ₈	N ₉	N ₁₀	N ₁₁	N ₁₂	N ₁₃	N ₁₄	
COM ₂	b _{C1}	F ₂	a ₂	b ₂	c _{0L}	F ₃	a ₃	b ₃	D _P	F ₄	a ₄	b ₄	C _F	F	
	d ₂	e ₂	G ₂	C ₂	d ₄	e ₃	G ₃	C ₃	d ₃	e ₄	G ₄	C ₄	OFF	C	COM ₁

* "OFF" signal is always being output at COM₁ side of N₁...



SERIAL OUTPUT:

TEMPERATURE DATA CONVERTED SERIALLY BY MD, SHCK INT, PUR TERKIALS
TEMPERATURE DATA IS OUTPUT AS TOTAL 15-BITS DATA



D1: °C POLARITY (1:MINUS 0:PLUS)

D2: °F (HUNDREDTH DIGIT) (°C NO USE)

D3: 80

D4: 40

D5: 20

D6: 10

D7: 8

D8: 4

D9: 2

D10: 1

D11: 0.8

D12: 0.4

D13: 0.2

D14: 0.1 SUNSTAR半导体集成电路 <http://www.icasic.com/> TEL: 0755-83387016 FAX:0755-83376182 E-MAIL: szss20@163.com

D15: (°C / °F) (0=°C 1=°F)

欢迎索取免费详细资料、设计选型指南和光盘、样品；产品繁多未能尽录，欢迎来电查询。

[中国传感器科技信息网：HTTP：//WWW.SENSOR-IC.COM/](http://WWW.SENSOR-IC.COM/)

[工控安防网：HTTP：//WWW.PC-PS.NET/](http://WWW.PC-PS.NET/)

[消费电子专用电路网：HTTP://WWW.SUNSTARE.COM/](http://WWW.SUNSTARE.COM/)

E-MAIL：xjr5@163.com szss20@163.com

MSN：suns8888@hotmail.com

QQ：195847376

地址：深圳市福田区福华路福庆街鸿图大厦 1602 室

电话：0755-83376549 83376489 83387030 83387016

传真：0755-83376182 83338339 邮编：518033 手机：(0)13902971329

深圳展销部：深圳华强北路赛格电子市场 2583 号 TEL/FAX：
0755-83665529 25059422

北京分公司：北京海淀区知春路 132 号中发电子大厦 3097 号

TEL：010-81159046 82615020 13501189838 FAX：010-82613476

上海分公司：上海市北京东路 668 号上海赛格电子市场 2B35 号

TEL：021-28311762 56703037 13701955389 FAX：021-56703037

西安分公司：西安高新开发区 20 所(中国电子科技集团导航技术研究所)
西安劳动南路 88 号电子商城二楼 D23 号

TEL：029-81022619 13072977981 FAX:029-88789382

成都：TEL:(0)13717066236

技术支持：0755-83394033 13501568376